Convoy H3 Operation

While Off

1 click - On (all brightness levels use memory except Moonlight)
Hold - Turn on in Moonlight level
2 clicks - Turbo
3 clicks - Strobe
4 clicks - Momentary Turbo (4 clicks to exit)
5 clicks - Battery Check (3 blinks…pause…7 blinks = 3.7 volts)
6 clicks - Change between Smooth and Stepped Ramping
10 clicks - Lockout (4 clicks to unlock)

While On

1 click - Off
Hold - Change brightness
2 clicks - Turbo
3 clicks - Strobe
5 clicks - Battery Check

Charging

The maximum charging current is 2A.

The USB C charging port is located in the front below the reflector. Remove the cover and insert cable (not included).

- Green light - Battery charged / no battery / battery disconnected
- Red light - Charging
- Orange light - Battery disconnected during charging

All brightness levels can be used while charging

- Thermal regulation triggers at 50°C

- Once the battery becomes low the output will drop to Low level and the switch LED will begin to flash red.

- Low voltage Protection is set at 2.8 volts and the flashlight will turn off.

What's Included:

- Convoy H3
- Pocket Clip
- Headband